

ASR-10 Quick guide

To record a sample

1. see instructions in studio how-to documentation

To truncate a sample

Truncating a sample deletes unused parts at the beginning and end

1. select **Edit > Wave**
2. Set sample start time (course % first then sample by sample of necessary)
3. Set sample end
4. Truncate wave by going **CMD > Wave > truncate wavesample**
5. Hit Enter

To save an instrument to Floppy

1. **CMD > Inst > Save instrument**
2. insert EPS formatted floppy and hit Enter

To format a floppy disk

1. **CMD > Sys > Erase and format disk**
2. hit Enter

To Load and Instrument from Floppy

1. Insert floppy
2. **Load > Inst**
3. scroll through instruments on disk and select the one you want
4. hit Enter
5. Select one of the 8 instruments slots for it to live in

To delete and instrument from a slot

1. Click and hold on the instrument slot
2. hit the Cancel button

To create and instrument keyboard range

1. select the instrument
2. **Edit > Inst**
3. Scroll to range option
4. position cursor over lowest note and hit note on keyboard
5. position cursor over highest note and hit note on keyboard

To create custom tunings

1. **CMD > Pitch**
2. Edit pitch table as described on pg. 249 of manual